

LRS-50 / LRS-100 / LRS-150-12


Switching Power Supply



LRS-50-12



LRS-100-12



LRS-150-12

Specifications

Model No.	LRS-50-12	LRS-100-12	LRS-150-12
Output-DC Voltage	DC 12V	DC 12V	DC 12V
Output-Rated Current	4.2A	8.5A	12.5A
Output-Rated Power	50.4W	102W	150W
Output-Voltage Adj. Range	10.2~13.8V	10.2~13.8V	10.2~13.8V
Input-Voltage Range	85~264VAC	85~264VAC	85~132VAC / 170~264VAC (selected by switch)
Input-Frequency Range	47~63Hz	47~63Hz	47~63Hz
Protection-Overload	110%~150%	110%~150%	110%~150%
Protection-Overvoltage	13.8~16.2V, Protection type: Hiccup mode, recovers automatically after fault condition is removed	13.8~16.2V, Protection type: Hiccup mode, recovers automatically after fault condition is removed	13.8~16.2V, Protection type: Hiccup mode, recovers automatically after fault condition is removed
Environment-Working Temp.	-30°C~ 70°C	-30°C~ 70°C	-30°C~ 70°C
Environment-Working Humidity	20~90 % RH non-condensing	20~90 % RH non-condensing	20~90 % RH non-condensing
Dimensions (L x W x H) mm	99 x 82 x 30	129 x 97 x 30	159 x 97 x 30

JM-5896-G Switching Adapter



Specifications

Input Voltage	100 -240VAC
Output DC Voltage	DC 12V
Output Rated Current	1A
Dimensions	52 x 21 x 12, Right Angle DC Power Plug